# Programming Guide

Programming a phone for internet and MMS doesn't have to be difficult! Simple Mobile provides the Over the Air (OTA) capability on the SMART portal for easy configuration. Occasionally you'll find a phone that needs to be manually configured. Just follow these step-by-step instructions to program Internet and MMS settings for a growing list of phones Simple Mobile customers like to use.

---

## Android 1.5 (HTC G1 & Samsung Behold II) - Internet and MMS

---

### For Samsung Behold II,dial *#87927# and skip to step 5.

1. Press the menu.
2. Tap Settings.
3. Tap Wireless Controls or Wireless & Networks.
4. Tap Mobile Networks.
5. Check that:
   - "Data Roaming" and "Use Only 2G Networks" are both unchecked.
6. Tap Access Point Names.
7. Press the menu button.
8. Select New APN.
   - Name:SIMPLE Mobile
   - APN: simple
   - Proxy:<Not set>
   - Port:<Not set>
   - Username:<Not set>
   - Password:<Not set>
   - Server:<Not set>
   - MMSC:http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
   - MMS Proxy:<Not set>
   - MMS Port:<Not set>
   - MCC: 310
   - MNC: 260
   - APN Type:<Not set>
   - If no APN settings are present, a restore to factory default settings may be required.

---

## Android 1.6 and Higher - Internet and MMS

---

From the home screen

1. Press Menu
2. Select "Settings"
3. Select "Wireless & networks"
   - Check that "Airplane mode" and "Wi-Fi" are unchecked
4. Select "Mobile networks"
   - Check that "Data enabled" is checked.
5. Select "Access Point Names"

6. Delete all existing APNs
   - Select APN
   - Press Menu
   - Select "Delete APN"
7. Create new APN
   - Press Menu
   - Select "New APN"
   - Enter the following information:
     - Name: SIMPLE Mobile
     - APN*: simple
     - Proxy: <Not set>
     - Port: <Not set>
     - Username: <Not set>
     - Password: <Not set>
     - Server: <Not set>
     - MMSC: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
     - MMS Proxy: <Not set>
     - MMS Port: <Not set>
     - MCC: 310
     - MNC: 260
     - Authentication Type: <Not set>
     - APN type: <Not set>
     - *Case sensitive
     - Press Menu
     - Select "Save"
8. Reboot phone.
9. Your Internet & MMS is now configured!

---

## Apple iPhone - Internet and MMS (All Models)

---

Cellular Data

1. Select Settings.
2. General Settings.
3. Select Network.
4. Select Cellular Data Network.
5. Select APN.
6. APN: simple
7. Username: Blank
8. Password: Blank

MMS

1. APN: simple
2. Username: blank
3. Password: blank
4. MMSC: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
5. MMS Proxy: blank
6. MMS Message Size: 1048576
7. MMS UA Prof URL:http://www.apple.com/mms/uaprof.rdf

## AT&T Quickfire - Internet and MMS

Internet Part 1

1. Press MENU.
2. Press SETTINGS.
3. Press PHONE.
4. Press NETWORK PROFILE.
5. Press ADD.
6. Title: Simple
7. Username: Blank
8. Password: Blank
9. APN: simple (lowercase)
10. Press SAVE two times then press END CALL.

Internet Part 2

1. Tap SETTINGS.
2. Tap APPS.
3. Tap BROWER SETTINGS.
4. Tap ADD.
5. Tap ENTER NAME: Simple
6. Hit DONE.
7. Home: http://www.google.com/
8. Hit DONE.
9. Proxy Address: 216.155.165.50
10. Port: 8080
11. Network Profiles: Select Simple and press Activate.

Internet Part 3

1. Tap MENU.
2. Tap SETTINGS.
3. Tap APPS.
4. Tap MSG SETTINGS and then MULTIMEDIA MESSAGES.
5. Tap MSG CENTER.
6. Verify the following:

- Name: Simple MMS
- MMSC URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
- MMSC Proxy: 216.155.165.050
- MMSC Port: 8080
- Network Profile : Simple (drop down list)

## Blackberry - Data Connectivity (without BIS services) MMS not supported

### Note: You must download a 3rd party browser to access the internet (see steps below).

Setting the APN

1. Select Options or Settings and then select Options.
2. Select Advanced Options.
3. Select TCP (Option will say TCP/IP on OS 4.6 and higher).

4. If applicable, check mark the APN Settings Enabled box.
5. Enter simple as the APN. Ensure no entries in the username or password fields.
6. Click the back arrow and then select Save.

Delete any existing Carrier Service Books

1. Select Options then select Advanced Options.
2. Scroll down and select Service Books.
3. Delete any listings for [browser configuration].
4. Back out and save the changes.

Opera Browser Download and Installation from a Blackberry Wi-Fi Connection:

1. Select the Manage Connections icon.
2. Checkmark the Wi-Fi checkbox.
3. Select Setup Wi-Fi.
4. Select Scan for Networks.
5. Connect to an available network.
6. Open the Browser icon.
7. Select Go to from the Blackberry menu key and go to http://mini.opera.com (NOTE: If the browser still says no network connection press the menu button, select Options-General, and switch to the Hotspot browser.
8. Download/install the Opera Mini browser.
9. Once installed, power cycle the Blackberry.

Opera Browser Download and Installation from a personal computer (make sure the Blackberry Desktop Manager software is installed):

1. Go to http://www.opera.com/mini.
2. Click the Download Opera Mini link.
3. Select your Blackberry model from the drop-down list.
4. (Note: If you don't see your specific Blackberry model, choose Opera Mini generic)
5. Follow the prompts and download the software to the desktop.
6. Right-click the downloaded software and select Extract All (a new, unzipped folder will appear on the desktop).
7. Plug the Blackberry in to the PC via USB cable connection.
8. Open the Blackberry Desktop Manager.
9. Click on the Application Loader icon.
10. Click the Browse button and browse to the downloaded and unzipped folder and then select the operette-hifi-en-us-nojsr75.alx file.
11. Click Next from the Blackberry Desktop Manager and follow the installation prompts.

GMAIL app Install

1. After installing the browser, go to http://gmail.com/app.
2. Click on "Open".
3. Message opens up "The application Opera Mini is attempting to invoke the browser to view m.google.com. Would you like to allow this?"
4. Click Yes.
5. Click on Download.

Google SYNC (Contacts and Calendar)

1. Go to http://m.google.com/sync
2. Click on "Install Now".
3. Follow any further instructions.

## LG Optimus T and Optimus G2X - Internet and MMS

1. Press Menu
2. Select Settings
3. Select Wireless & Networks
   - Check that Airplane mode is **unchecked**
4. Select Mobile Networks
   - Check that Data Enabled is **checked**
5. Select Access Point Name
   - ***Note*** T-Mobile US APN cannot be edited or delete
   - Press Menu
   - Select New APN
   - Enter the following settings:
     - Name:SIMPLE Mobile
     - APN*:simple
     - Proxy:<Not set>
     - Port:<Not set>
     - Username:<Not set>
     - Password:<Not set>
     - Server:<Not set>
     - MMSC: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
     - MMS Proxy:<Not set>
     - MMS Port:<Not set>
     - MCC: 310
     - MNC: 260
     - Authentication Type: <Not set>
     - APN type:<Not set>
     - *Case sensitive
   - Press Menu
   - Select Save
6. Make sure the green radio button is directly to the right of SIMPLE Data MMS
7. Reboot phone.
8. Your Internet & MMS is now configured!

## LG Generic (Sentio GS505, GS170, DLite) - Internet and MMS

Many LG devices can simply be programmed Over the Air. Please contact your local Dealer to receive your OTA programming message.

Internet Setup

1. Select Menu.
2. Select Settings.
3. Select Connection.
4. Select Network Profile.
5. Select Network Profile.
6. Enter the following information:
   - Connection title: simple web

- Auth: [None]
- User name: [empty]
- Password: [empty]
- APN: simple

Browser Setup

1. Select Menu.
2. Select Media Net (if At&t).
3. Select Browser Settings.
4. Select Accounts.
5. Select Options.
6. Select New.
7. Enter the following details:
   - Acct Name: Simple Web
   - Homepage: [User Preference]
   - Connection Type: TCP without proxy
   - Security: Non-Secure
   - Time out: 150
   - Network profile: Simple Web
   - Click Save
   - Check the box next to Simple Web

MMS setup

1. Select Messages.
2. Select Message Settings.
3. Select MMS.
4. Select message Center.
5. Select Options.
6. Select New.
7. Enter the following information:
   - Name: Simple MMS
   - MMSC URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
   - MMSC Proxy: 0.0.0.0
   - MMSC Port: 80
   - Connection Mode: TCP w/o Proxy
   - Network Profile: Simple Web
   - Click Save
   - Select Activate

---

## LG KP500

---

Internet Setup

1. Select Menu.
2. Select Settings.
3. Select Connection.
4. Select Access points.
5. Add profile.
6. Connection title enter: Simple Mobile
7. Bearer: GPRS

8. Authentication: PAP
9. Username: NONE
10. Password: NONE
11. APN enter: simple
12. Connection title enter: Simple Mobile
13. Save
14. Back to Connectivity.
15. Internet profiles.
16. Add profile.
17. Title enter: Simple WEB
18. Use proxy: On
19. Proxy server address: 216.155.165.050
20. Proxy server port: 8080
21. Access point: Simple mobile
22. Save
23. Go to the internet.
24. Settings.
25. Profiles.
26. Add profile
27. Title: Simple
28. Internet profile
29. SimpleWEB
30. Save.
31. Activate Simple WEB.

MMS Setup

1. Select Menu.
2. Select Settings.
3. Select Connectivity.
4. Select Internet profiles.
5. Add profile.
6. Title: Simple MMS
7. Use proxy: On.
8. 216.155.165.050
9. Proxy server port: 8080
10. Access point: Simple Mobile
11. Multi msg center
12. Add center
13. Title: Simple MMS
14. MMSC URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
15. MMS profile
16. Simple MMS
17. Save, then press "Yes" to activate.

---

## Samsung Galaxy S (3G, 4G)

---

From the home screen

1. Press Menu

2. Select "Settings"
3. Select "Wireless and networks"
- Check that "Flight Mode" is unchecked

4. Select "Mobile Networks"
- Check that "Use packet data" is checked

5. Select "Access Point Names"
6. Press Menu
- Select "Reset to default"

7. Select "T-Mobile US"
- Select "Name" and populate the field with "SIMPLE Data MMS" (not required)
  - Select "OK"
- Select "APN" and populate the field with "simple" ***CASE SENSITIVE***
  - Select "OK"
- Select "MMSC" and add "smpl." after "http://" and before "mms."
  - Field should show "http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc"
  - Select "OK"
- Press Menu
  - Select "Save"

8. Reboot phone.
9. Your Internet and MMS is now configured!

---

## Samsung Gravity (1,2,3,T) and Most Samsung Devices - Internet and MMS

---

Many Samsung devices can simply be programmed Over the Air. Please contact your local Dealer to receive your OTA programming message.

Internet

1. Dial*#87927#
2. Choose a profile to edit
3. Press Options
4. Select Edit
5. Enter the following settings
- Set name:Simple WEB
- Access name: simple
- Auth Type:Normal
- User ID:blank
- Password: blank
- Protocol:HTTP
- Home URL:http://www.google.com/
- Proxy Address: 216.155.165.50
- Port: 8080
- Linger Time(Sec.): 300

6. Press Save.
7. Radio dot should be on the right of Simple WEB

MMS

1. Dial*#87667#
2. Press create
3. Enter the following settings

- Set name:Simple MMS
- Access name: simple
- Auth type:Normal
- User ID:blank
- Password:blank
- Protocol:HTTP
- Home URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
- Proxy address: 0.0.0.0
- Linger Time: 300

4. Press Save.
5. Radio dot should be on the right of Simple MMS

---

## Samsung Behold (Highlight, Memoir & Solstice) - Internet and MMS

---

### Many Samsung devices can simply be programmed Over the Air. Please contact your local Dealer to receive your OTA programming message.

Internet

1. *#6984125*#
2. In the Admin setting.
3. Network & call settings.
4. Connections.
5. Network profiles menu, you will need to delete the DM Profile and the TMO_DS profile.
6. Name: SimpleMobile
7. APN or Access Point : simple
8. Proxy: 216.155.165.050
9. Home URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
10. Port: 8080
11. Linger Time: 3003
12. Auth Type: Not Set or empty
13. Internet (you will need to edit the Browser Profile).

MMS (you will need to edit the MMS profile)

1. Name: Simple MMS
2. Access name: simple
3. Proxy: 216.155.165.050:8080
4. Home URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc

---

## Samsung A-Series Phones - Internet and MMS Setup

---

### Many Samsung devices can simply be programmed Over the Air. Please contact your local Dealer to receive your OTA programming message.

Internet

1. Menu.
2. Settings.
3. Application Settings.
4. Browser Settings.
5. Options.

6. New.
7. Set Name: Simple Web
8. Access Name: simple (All Lowercase)
9. Auth Type: none
10. User ID: blank
11. Password: blank
12. Protocol: HTTP
13. Home URL: http://www.google.com/
14. Proxy Address: 216.155.165.050
15. Port: 8080
16. Linger Time: 3003
17. Save
18. Highlight Simple Web and Save.

MMS

1. Menu.
2. Settings.
3. Application Settings.
4. Messaging Settings.
5. Multimedia Message.
6. Multimedia Message Profiles.
7. Options.
8. New.
9. Set Name: Simple MMS
10. AcAuth Type: Secure
11. User ID: blank
12. Password: blank
13. Protocol: HTTP
14. Home URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
15. Proxy Address: 216.155.165.050
16. Port: 8080
17. Linger Time: 3003
18. Save
19. Highlight Simple MMS and Save.

---

## Samsung T-Series Phones - Internet and MMS

---

Many Samsung devices can simply be programmed Over the Air. Please contact your local Dealer to receive your OTA programming message.

Internet Setup

1. Enter *#87927#
2. Name: Simple Web
3. APN: simple
4. Auth Type: none
5. Username: blank
6. Password: blank
7. Protocol: HTTP
8. Home URL: http://www.google.com/

9. Proxy Address: 216.155.165.050
10. Proxy Port: 8080 (If there is no field for the port add ":8080" at the end of the proxy address)
11. Linger Time: 3003
12. Save

MMS Setup

1. Enter *#87927#
2. Select MMS.
3. Name : Simple MMS
4. APN: simple (All lowercase)
5. Auth Type: Secure
6. Username: blank
7. Password: blank
8. Protocol: HTTP
9. Home URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
10. Proxy Address: 216.155.165.050
11. Proxy Port: 8080 (If there is no field for the port add ":8080" at the end of the proxy address)
12. Linger Time: 3003
13. Save

Alternative Internet Setup

1. Enter *#87927#
2. Select Profile Settings.
3. Choose an empty profile to edit the settings on, usually Profile 2.
4. Name : Simple Web
5. Home URL: http://www.google.com/
6. Proxy Enabled.
7. Auth Type: none
8. Username: blank
9. Password: blank
10. Protocol: HTTP
11. Select GPRS Settings
12. Proxy Address: 216.155.165.050
13. Proxy Port: 8080
14. APN or Access Point: simple (All lowercase)
15. Save
16. Save again.
17. Go back to the screen where it says Current Profile and Profile Settings.
18. Select Current Profile.
19. Highlight Simple Web then press save.

Alternative MMS Setup

1. Enter *#87667#
2. Select Profile Settings.
3. Choose an empty profile to edit the settings on, usually Profile 2.
4. Name : Simple MMS
5. Home URL: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
6. Proxy Enabled.
7. Auth Type: Secure
8. Protocol: HTTP
9. Username: blank

10. Password: blank
11. Select GPRS Settings
12. Proxy Address: 216.155.165.050
13. Proxy Port: 8080
14. APN or Access Point: simple (All lowercase)
15. Save
16. Save again.
17. Go back to the screen where it says Current Profile and Profile Settings.
18. Select Current Profile.
19. Highlight Simple Web then press save.

---

## Sciphone (iPhone clone) - Internet and MMS

---

Internet Setup

1. Select Menu, Services, Data Account, and then select GPRS.
2. Select the first profile (China Mobile) and then select Edit.
3. Enter the appropriate settings as shown below:
   - Name: simpleweb
   - Access Point (APN):simple
   - Connection Type: http
   - User Name: none
   - Password: none
4. Select Options and then select Done.
5. Select Services, WAP, and then select Settings.
6. Select Edit Profile, SIM 1, and then Edit the first profile in the list.
7. Enter the appropriate settings as shown below:
   - Name: simpleweb
   - Homepage:http://www.google.com
   - Data Account: simpleweb
   - Connection Type: http
   - **The following settings may not appear**
   - Proxy: 0.0.0.0
   - Port: 80
   - User Name: none
   - Password: none

MMS Setup

1. Select Messages and then select Message Settings.
2. Select Server Profile, and then Edit the first profile in the list.
3. Enter the appropriate settings as shown below:
   - Name: simpleweb
   - Homepage: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
   - Data Account: simpleweb
   - Connection Type: http
   - **The following settings may not appear**
   - Proxy: 0.0.0.0
   - Port: 80
   - User Name: none

- Password: none

4. Select Options and then select Done.
5. Highlight the new profile and then select Activate.

---

## Nokia Devices

---

Many Nokia devices can simply be programmed Over the Air. Please contact your local Dealer to receive your OTA programming message.

Generic Internet Setup

1. From the main menu select Settings.
2. Select Configuration settings.
3. Select Personal configuration settings.
4. Select Add New.
5. Select Services (or Web).
6. Select Account name.
7. Enter Simple.
8. Select OK.
9. Select Homepage and enter: http://www.google.com
10. Select OK twice.
11. Leave the Username and Password blank.
12. Select Access point settings.
13. Select Proxy.
14. Select Disable.
15. Select OK.
16. Select Proxy address.
17. Enter 0.0.0.0
18. Select OK.
19. Select Proxy Port.
20. Enter 8080 and then select OK.
21. Select Data bearer.
22. Select GPRS and then select OK.
23. Select Bearer settings.
24. Select GPRS access point.
25. Enter simple as the access point and then select OK.
26. Select Authentication.
27. Select Normal and then select OK.
28. Leave the Username and Password blank.
29. Select Back twice.
30. Select the Simple profile.
31. Select Options.
32. Select Activate Service Settings.
33. Press the red End key to return to the home screen.

---

## Nokia 5230

---

Internet Setup

1. Menu.
2. Settings.
3. Connectivity.
4. Destinations.
5. Internet.
6. Options.
7. New access point.
8. Tap on No.
9. Tap on Packet data.
10. Tap on the Text field.
11. Enter Simple Web and then tap on the Green check mark.
12. Tap on OK.
13. Highlight the Simple Web and then tap on Options.
14. Tap on Edit.
15. Tap on Access point name.
16. Enter "simple" and tap on the Green check mark.
17. Tap on OK.
18. Tap on Homepage.
19. Enter http://www.google.com/ and then tap on the Green check mark.
20. Tap on OK.
21. Tap on Options.
22. Tap on Advanced settings.
23. Tap on Proxy server address.
24. Enter 216.155.165.050 and tap on the Green check mark.
25. Tap on OK.
26. Tap on Proxy port number.
27. Enter 8080 and tap on the Green check mark.
28. Tap on OK.
29. Tap on Back until you reach the Main menu screen.
30. Tap on the Internet icon.
31. Tap on the Web icon.
32. Tap on Options.
33. Tap on Settings.
34. Tap on General.
35. Tap on Access point.
36. Tap on Internet and tap on Options.
37. Tap on Select access point.
38. Highlight Simple Web and then tap on OK.
39. Your manual internet will now be configured and set as default.

MMS Setup

1. Menu.
2. Settings.
3. Connectivity.
4. Destinations.
5. Multimedia msg.
6. Options.
7. New access point.
8. Tap on No.

9. Tap on Packet data.
10. Tap on the Text field.
11. MMS.
12. Enter Simple and then tap on the Green check mark.
13. Tap on OK.
14. A new Access point is added.
15. Highlight the new access point and then tap on Options.
16. Tap on Edit.
17. Tap on Access point name.
18. Enter "simple" and tap on the Green check mark.
19. Tap on OK.
20. Tap on Homepage.
21. Text field.
22. Enter: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
23. Tap on OK.
24. Tap on Options.
25. Tap on Advanced settings.
26. Tap on Proxy server address.
27. Enter 216.155.165.050 and tap on the Green check mark.
28. Tap on OK.
29. Tap on Proxy port number.
30. Enter 8080 and tap on the Green check mark.
31. Tap on OK.
32. Tap on Back until you reach the Main menu screen.
33. Tap on the Messaging icon.
34. Tap on Options.
35. Tap on Settings.
36. Tap on Multimedia Message..
37. Tap on Access point.
38. Tap on MMS.
39. Tap on Simple OK.

---

## HTC MyTouch (4G, 3G Slide, 3G) - Internet and MMS

---

From the home screen

1. Press Menu
2. Select "Settings"
3. Select "Wireless & networks"
   - Check that "Airplane mode" is unchecked and "Mobile network" is checked
4. Select "Mobile Networks"
5. Select "Access Point Names"
6. Press Menu
   - Select "Reset to Default"
7. Select "T-Mobile Data"
   - Select "Name" and populate the field with "SIMPLE Data"
   - Select "OK"
   - Select "APN" and populate the field with "simple" *CASE SENSITIVE*

- Select "OK"
- Press Menu
- Select "Save"

8. Select "T-Mobile MMS"
- Select "Name" and populate the field with "SIMPLE MMS"
- Select "OK"
- Select "APN" and populate the field with "simple" *CASE SENSITIVE*
- Select "OK"
- Select "MMSC" and add "smpl." after "http://" and before "mms."
- Field should show "http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc"
- Select "OK"
- Press Menu
- Select "Save"

9. Reboot phone.
10. Your Internet & MMS is not configured!

---

## HTC Dash (Windows Phone & Windows Mobile) - Internet Setup

---

Internet Setup

1. Click on Start.
2. Select Settings.
3. Select Connections.
4. Select GPRS (DELETE ALL T-MOBILE OPTIONS).
5. Select New and enter the following information:
- Name: Simple
- Connect to: Internet
- Access point name: simple
- Username: Blank
- Password: Blank
- Primary dns: Blank
- Secondary dns: Blank
- IP address: Blank

6. Press Done.
7. Start.
8. Internet Explorer.
9. Menu.
10. Tools.
11. Options.
12. Connections.
13. "Automatically Detect Settings" should be Checked.
14. Done.

---

## HTC HD2 - Internet and MMS

---

Internet Setup

1. From the home screen scroll to Settings.

2. Select Wireless Controls.
3. Select Menu on the bottom right.
4. Select Connections.
5. Select Advanced.
6. Select "Select Networks".
7. Select New.
8. Enter "Simple Mobile" in the field.
9. Select Modem.
10. Select New.
11. Enter "Simple Web" in the field - enter a name for the connection.
12. Select "Cellular Line (GPRS)" in the field "Select a Modem".
13. Enter "simple" in the field "Access point name".
14. Leave User name/Password/Domain blank.
15. You should now see a black dot in front of Simple Web. Select OK on the top right.
16. Ensure "Simple Mobile" is selected for both drop down menus.
17. Your internet is now configured.

MMS Setup

1. From the home screen select the "Messages" application.
2. Select Menu in the bottom right.
3. Select Settings.
4. Select Options.
5. Select Menu in the bottom right.
6. Select MMS Server.
7. Select New.
8. Enter the following:
   - Name: Simple MMS
   - IP Address: blank
   - Port number: blank
   - Server Address: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
   - Connect via: Simple Web
   - Message size limit: 1024 KB
9. Select and hold down Simple MMS.
10. Select Set as Default.
11. There should be a green dot marked on the right of Simple MMS.
12. Your MMS is now configured.

---

## HTC G1 and G2 - Internet and MMS

---

Internet Setup

1. Press the menu button (on front of phone).
2. Tap Settings.
3. Tap Wireless Controls.
4. Tap Mobile Networks.
5. Tap Access Point Names.
6. Press the menu button.
7. Select New APN.
8. Enter the following details:

- Name: Simple
- APN: simple
- Proxy: <Not set>
- Port: <Not set>
- Username: <Not set>
- Password: <Not set>
- Server: <Not set>
- MMSC: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
- MMS Proxy: <Not set>
- MMS Port: <Not set>
- MCC: <Not set>
- MNC: <Not set>
- APN Type: <Not set>

---

## HTC HD7 - Internet only

---

1. Press the right arrow
2. Select settings
3. Select cellular
4. Select edit apn
5. Enter the following settings:
   - APN: simple
   - User name:blank
   - Password:blank
   - Press the check mark
6. Your internet is configured!

---

## HTC Touch Pro 2

---

Internet Settings

1. Select Start
2. Select Settings
3. At the bottom left corner, select All Settings
4. Select the connections folder
5. Select the connections icon
6. Select New
7. For the Name of the Connection, enter Simple Web
8. For Select a Modem, use Cellular Line (GPRS, 3G), do NOT use just Cellular line
9. Select Next
10. For Access Point Name, enter simple in all lowercase letters.
11. Select Next
12. Leave Username, Password, and Domain blank and select Finish
13. Tap and hold on Simple Web and select Connect.
14. Exit to the home screen.

Picture Message Settings

1. Select Start

2. Select Text
3. In the lower right corner, select Menu
4. Select MMS Options
5. At the bottom of the screen, select the Servers tab
6. Select New
7. Enter the following information,
8. Server Name: Simple MMS
9. Gateway:216.155.165.50
10. Port Number: 8080
11. Server Address: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
12. Connect Via: Simple Web*
13. Send Limit: *Leave as default* (300k)
14. Select Done
15. Highlight Simple MMS and select Set As Default

---

## Google Nexus One & Nexus S - Internet and MMS

---

From the home screen

1. Press Menu
2. Select "Settings"
3. Select "Wireless & networks"
- Check that "Airplane mode" and "Wi-Fi" are unchecked

2. Select "Mobile networks"
   - Check that "Data enabled" is checked.
3. Select "Access Point Names"
4. Delete all existing APNs
   - Select APN
   - Press Menu
   - Select "Delete APN"
5. Create new APN
   - Press Menu
   - Select "New APN"
   - Enter the following information:
     - Name: SIMPLE Mobile
     - APN*: simple
     - Proxy: <Not set>
     - Port: <Not set>
     - Username: <Not set>
     - Password: <Not set>
     - Server: <Not set>
     - MMSC: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
     - MMS Proxy: <Not set>
     - MMS Port: <Not set>
     - MCC: 310
     - MNC: 260
     - Authentication Type: <Not set>
     - APN type: <Not set>

- *Case sensitive

6. Press Menu
7. Select "Save"

4. Reboot phone.
5. Your Internet & MMS is now configured!

---

## Motorola RAZR v3 - Internet and MMS

---

Many Motorola devices can simply be programmed Over the Air. Please contact your local Dealer to receive your OTA programming message.

WAP Setup

1. Enter the Main Menu.
2. Select Settings.
3. Select Web Access.
4. Select Web Sessions.
5. Select New Entry.
6. Enter the following information:
   - Name: Simple
   - Homepage: [Up to the customer]
   - Proxy 1: 0.0.0.0
   - Port 1: 8080
   - Domain 1: [empty]
   - DNS1: [empty]
   - DNS2: [empty]
   - GPRS APN: simple
   - Username: [empty]
   - Password: [empty]
7. Select Done.
8. With Simple highlighted, select Options Set as Default.

MMS Setup

1. Enter the Main Menu.
2. Select Messaging.
3. Select Options.
4. Select Setup.
5. Select Message Setup.
6. Select Multimedia Message Setup.
7. Select Server Info.
8. Select Options.
9. Select New.
10. Enter the following details:
    - Service Name: Simple MMS
    - Server name: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
    - Web Session Name: select Simple
11. Select Done.
12. Select simple mms and there will be a check next to it that indicates it will be using that mms profile.

# Motorola CLIQ (XT & 2) - Internet and MMS

From the home screen

1. Press Menu
2. Select "Settings"
3. Select "Wireless & networks"

- Check that "Airplane mode" and "Wi-Fi" are unchecked

2. 4 Select "Mobile networks"

- Check that "Data enabled" is checked.

3. 5 Select "Access Point Names"
4. 6 Delete all existing APNs

- Select APN
- Press Menu
- Select "Delete APN"

5. Create new APN

- Press Menu
- Select "New APN"
- Enter the following information:
  - Name: SIMPLE Mobile
  - APN*: simple
  - Proxy: <Not set>
  - Port: <Not set>
  - Username: <Not set>
  - Password: <Not set>
  - Server: <Not set>
  - MMSC: http://smpl.mms.msg.eng.t-mobile.com/mms/wapenc
  - MMS Proxy: <Not set>
  - MMS Port: <Not set>
  - MCC: 310
  - MNC: 260
  - Authentication Type: <Not set>
  - APN type: <Not set>
  - *Case sensitive

6. Press Menu
7. Select "Save"